Cleaver Brooks CB-Packa	aged Firetube Boiler- 60 HP
Mfg: Cleaver Brooks	Model: CB200-60
Stock No. 85.D001	Serial No <sub>.</sub> L-69074

Cleaver Brooks CB-Packaged Firetube Boiler- 60 HP. Model: CB200-60. S/N: L-69074. Input: 2,511,000 BTU/HR. Maximum pressure: 30HW psi. Fuel: Gas-Oil. Burner: 4A natural gas. Oil type: 4A. Oil supply: 0.3 gpm (18 gph). Power supply: 460 V, 7 amps, 60 Hz, 3 phase. Minimum circuit ampacity: 8 amps. Maximum circuit protection 28 amps.

Cleaver Brooks Motor, 2 and 1-1/2 hp, 3510/2850 rpm, 200-230/460-190/380 V, 5.8-5.4/2.7-5.0/2.5 amps, 60/50 Hz, 3 phase.

A Firetube boiler is a cylindrical vessel, with the flame in the furnace and the combustion gases inside the tubes. The furnace and tubes are within a larger vessel containing the water which is converted to steam or hot water for process applications or hydronic comfort heating. Hot water is commonly used in heating applications with the boiler supplying water to the system at 180 °F to 220 °F. The operating pressure for hot water heating systems usually is 30 psig to 125 psig.

Inlets: (2) 5 in. dia. flanged ports. Outlets: (1) 10 in. dia. flanged port, (1) 2 in. dia. NPT fitting (relief valve), (1) 1 in. dia. low water cut off port, (1) 2 in. dia. drain port. Overall dimensions: 10 ft. 10 in. L x 6 ft. 11 in. W x 6 ft. 9 in. H.







































































MODEL ESSOS	SERIAL	NO. [ 1,=600]	14
MAX. PRESSURE	PSI PSI	DATE 5/	26280
NPUT 2544 004	STU/HR	GAS I	SPH OIL
ELECTRIC	AL REG	UIREME	NTS
MAIN POV	VER SUPPL	Y	
	LTS PH	HZ T	AME
MINIMUM CIRC	UIT AMPACITY	AM	P
MAX. RATING	OF CIRCUIT PROT	ECTION 24	AMP
BLOWER MOTO	IR I	HP	
AIR COMPRESS	SOR MOTOR	NP .	
OIL HEATER	KW		
CONTROL 120 VOLTS 1	CIRCUIT		
O11 D1144	MOTOR		
V	OLTS PH	HZ 9	AMP
	CLEAVER BRECKS DI	NIGHT .	77/14







